

Main Menu	Level 1	Level 2	Level 3	Level 4	Level 5	
Personality	Address	1-497	001* - (xxx)			
	DMX Mode	1.Standard 3-Zone*				
		2.Compressed 8-Bit				
		3.Compressed 16-Bit				
		4.Pixel RGB 8-Bit				
		5.Pixel RGBW 8-Bit				
		6.Pixel RGBW 16-Bit				
	ArtNET	Control Protocols	Disable*			
			Enabled on IP 2.x.x.x	Artnet on 2.x.x.x		
			Enabled on IP	Artnet on 10.x.x.x		
			Enabled on Custom	Custom IP		
		Control Protocol	Artnet			
			sACN			
		Repeat on DMX	Disabled*			
			Enabled on primary			
		Universe	Universe *000	0-255		
		Custom IP Addr	IP Addr byte 1 000	0-255		
			IP Addr byte 2 000	0-255		
			IP Addr byte 3 000	0-255		
			IP Addr byte 4 000	0-255		
		Custom IP Mask	IP mask byte 1 000	0-255		
			IP mask byte 2 000	0-255		
			IP mask byte 3 000	0-255		
	IP mask byte 4 000		0-255			
	Dimmer Curve	Standard*				
		Linear				
		Theatrical				
		Square Law				
		Inverse Square				
	Dimmer Speed	Fast				
		Smooth*				
		Ultra Smooth				
	PWM Rate Setting	600 Hz				
		1200 Hz*				
		2000 Hz				
		2400 Hz				
		12000 Hz				
		24000 Hz				
		30000 Hz				
	Cooling Mode	Auto*				
		Whisper				
		Silent				
		Standard				
		High power				
	Motor Settings	Tilt	Speed / Time mode	*Speed Time		
		Invert	Tilt Invert	Off* On		
			Zoom Invert	Off* On		
		Feedback	On*			
			Off			
		Home position	Tilt	0-255 (Default 128)		
Reset via DMX	On*					
	Off					

Main Menu	Level 1	Level 2	Level 3	Level 4	Level 5
Personality	Display Settings	Brightness	1-10 (Default 5)		
		On* / Off	Cancel* / Confirm		
		Shut-off time	Off*		
			2 minute		
			3 minute		
			4 minute		
			5 minute		
			10 minute		
			15 minute		
			20 minute		
			30 minute		
		40 minute			
	50 minute				
	60 minute				
	No signal flash	On*			
		Off			
	Flip Display	Auto*			
		Off			
		On			
	Temperature Unit	Celsius *			
Fahrenheit					
No DMX	Shutter Closed*				
	Hold				
Fixture ID	Disabled*				
	Set	1-255			
Lock	*Off				
	On				
	Set password	****	****		
Stand-Alone	Test Sequence	Dynamic*	Cancel*		
			Run		
	Static	Cancel*			
		Run			
	Master / Slave	Alone*	confirm		
		Master	confirm		
		Slave	Slave 1*		
			Slave 2		
	Slave 3				
	Static Mode	Tilt	0-255		
		Tilt Fine	0-255		
		Speed	0-255		
		Power/Special	0-255		
		Color Wheel	0-255		
		Red All	0-255		
		Green All	0-255		
		Blue All	0-255		
		White All	0-255		
		CTC All	0-255		
		Pattern Effects	0-255		
		Pattern Effect Speed	0-255		
		Pattern Effect Fade	0-255		
		Zoom	0-255		
		Shutter/Strobe	0-255		
		Dimmer	0-255		
	Reset All	Yes			
		No			

Main Menu	Level 1	Level 2	Level 3	Level 4	Level 5
Service	Reset	Fixture Reset	No*		
			Yes		
		Tilt Reset	No*		
			Yes		
		Zoom Reset	No*		
			Yes		
	Factory Default	Load	No*		
			Yes		
	Calibration Setting	Tilt	0-255		
		Zoom	0-255		
		LED 1	0-255		
		LED 2	0-255		
		LED 3	0-255		
		LED 4	0-255		
		LED 5	0-255		
		LED 6	0-255		
		LED 7	0-255		
LED 8		0-255			
Calibration Default		Motors Cal. Default	Load	No*	
		LED Cal. Default	Load	No*	
Color Calibration & Droop	On*			Yes	
		Off		Yes	
Advanced Settings (Input Password)	RDM Function	Enable			
		Disable*			
	Setup fixture model	No*			
		Yes			
	Firmware Update	Update this fixture	New firmware update	Update from PC	No*
			Update selected module		Yes
Update other fixture	Update selected module				
Information	Fixture time	Power On Time	Resettable	xxx Hours	
			Total	xxx Hours	
			Clear Resettable	Clear / Cancel	
		LED On Time	Resettable	xxx Hours	
			Total	xxx Hours	
			Clear Resettable	Clear / Cancel	
	Fixture Temp.	LED Board	Actual	xxx C / F	
			Max	xxx C / F	
			Reset Max	Cancel*/Confirm	
	Fan Speed (RPM)	LED Driver	(See above)	(See above)	
			Fan 1	xxxx Rpm	
			Fan 2	xxxx Rpm	
			Fan 3	xxxx Rpm	
	Fan 4	xxxx Rpm			
	Firmware version	x.x.x.x			
Serial Number	xxxxxxxxxx				
Product ID	Model Name	S850Z Batten			
Error Log	Load	No*			
		Yes			
Clear	No*				

Main Menu	Level 1	Level 2	Level 3	Level 4	Level 5
Information	Error Log	Clear	Yes		
	Network Parameters	IP Addr:	XXXXXXXXXX		
		NetMask	XXXXXXXXXX		
		MAC Address	XXXXXXXXXX		
	RDM Information	UID	XXXXXXXXXX		
Label		XXXXXXXXXX			
DMX Live	DMX Refresh rate	xxx Hz			
	Tilt	0-255			
	Tilt Fine	0-255			
	Speed	0-255			
	Power / Special	0-255			
	Color Wheel	0-255			
	Red All	0-255			
	Red Fine All	0-255			
	Green All	0-255			
	Green Fine All	0-255			
	Blue All	0-255			
	Blue Fine All	0-255			
	White All	0-255			
	White Fine All	0-255			
	CTC All	0-255			
	Pattern Effects	0-255			
	Pattern Effect Speed	0-255			
	Pattern Effect Fade	0-255			
	Zoom	0-255			
	Zoom Fine	0-255			
Shutter/Strobe	0-255				
Dimmer	0-255				
Dimmer Fine	0-255				